

## CLWM SERIES

### Wide Mouth Crimp Lugs



When a bell mouth crimp lug is used in conjunction with a flexible conductor, it is recommended to use the same size crimp lug as per the conductor. i.e. use CLWM120 (120mm<sup>2</sup>) crimp lug with 120mm<sup>2</sup> flexible cable. For crimping 6mm<sup>2</sup> to 120mm<sup>2</sup> lugs you can use either a manual tool or 13 tonne hydraulic crimp tool. For 150mm<sup>2</sup> flexible conductors and above, use a 23 tonne hydraulic tool.

For easier termination of fine stranded cables. **Compliant with Standard AS/NZS 4325.**

Code	Cable Size (mm <sup>2</sup> )	Stud Size ø (mm)
CLWM6M6	6	6
CLWM6M8	6	8
CLWM6M10	6	10
CLWM10M6	10	6
CLWM10M8	10	8
CLWM10M10	10	10
CLWM16M6	16	6
CLWM16M8	16	8
CLWM16M10	16	10
CLWM25M6	25	6
CLWM25M8	25	8
CLWM25M10	25	10
CLWM35M8	35	8
CLWM35M10	35	10
CLWM35M12	35	12
CLWM50M8	50	8
CLWM50M10	50	10

Code	Cable Size (mm <sup>2</sup> )	Stud Size ø (mm)
CLWM50M12	50	12
CLWM70M8	70	8
CLWM70M10	70	10
CLWM70M12	70	12
CLWM95M8	95	8
CLWM95M10	95	10
CLWM95M12	95	12
CLWM120M10	120	10
CLWM120M12	120	12
CLWM150M10	150	10
CLWM150M12	150	12
CLWM185M12	185	12
CLWM185M16	185	16
CLWM240	240	(blank)
CLWM300	300	(blank)
CLWM400	400	(blank)

## BF SERIES

### Bootlace Ferrules Non-Insulated



For easier termination of fine stranded cables.

Code	Cable Size (mm <sup>2</sup> )	Length
BF1.0/10	1.0	10.0 - 12.0
BF1.5/10	1.5	10.0 - 12.0
BF2.5/10	2.5	10.0 - 12.0
BF4.0/10	4.0	10.0 - 12.0
BF6.0/10	6.0	10.0 - 12.0
BF10/18	10.0	12.0 - 18.0
BF16/18	16.0	12.0 - 18.0
BF25/18	25.0	18.0 - 20.0

Code	Cable Size (mm <sup>2</sup> )	Length
BF35/18	35.0	18.0 - 20.0
BF50/18	50.0	18.0 - 20.0
BF70/25	70.0	25.0 - 32.0
BF95/25	95.0	25.0 - 32.0
BF120/30	120.0	30.0 - 32.0

*Length may vary depending on stock.*