

## Managing Electricity in Campgrounds & Holiday Parks

### Coin/ Token Operated Meter

The ET30KL meter is a 30 Amp coin or token operated electronic timer.

- ▶ High impact ABS case
- ▶ LCD display shows remaining credit
- ▶ Credits can be set from 1 second to 99 hours and 59 minutes
- ▶ Can operate by tokens or 50¢ or \$1.00 coins for a set time period
- ▶ Single coin/ token or pre-set tariff per session
- ▶ Override key-switch for match play and maintenance is included.
- ▶ Credit save facility

### ADDITIONAL INFORMATION

- ▶ Multi coin capable; each coin adds preset time to total (e.g. 5+5+5 minutes)
- ▶ Auto 'Coin Box Full' notification

### USES

- ▶ Showers and laundry facilities
- ▶ Sports indoor and outdoor court lighting
- ▶ Public facilities

### CHARACTERISTICS:

**Input Voltage** 230V AC

**Switching capacity (at 240V AC)** 7000 VA resistive

**Power consumption** 22 watts maximum

**Dimensions** 270mm x 183mm x 93mm (HxWxD)

**Weight** 1.4kg

**Case material** High impact ABS

**Override switch option** (for match play etc) Key operated (now included)

**Standards conform to** EN 60730-1:1992 including part 2.7

**1989 EMC directive Generic Standards** EN50081-1, EN50082-1



*This meter is intended for use with fixed wiring only.*

Code	Description
<b>ET30KL</b>	Coin/Token Operated Meter
<b>ET30TOKEN</b>	Tokens
<b>ET30CK50</b>	50c Coin Conversion Kit
<b>ET30CK1.00</b>	\$1.00 Coin Conversion Kit



### Convert unit to accept coins

ET30KL unit comes as a token timer, however it can be converted to accept 50¢ or \$1.00 coins. All you need to do is advise which coin and the time your customer would like it preset to. Conversion kits are an additional cost.